

Appendix E Guidelines to Rule 35

The following are guidelines to Rule 35.

The radial clearances shown below are minimum clearances that should be established, at time of trimming, between the vegetation and the energized conductors and associated live parts where practicable. Vegetation management practices may make it advantageous to obtain greater clearances than those listed below:

A. Radial clearances for any conductor of a line operating at 2,400 or more volts, but less than 72,000 volts 4 feet

B. Radial clearances for any conductor of a line operating at 72,000 or more volts, but less than 110,000 volts 6 feet

C. Radial clearances for any conductor of a line operating at 110,000 or more volts, but less than 300,000 volts 10 feet

D. Radial clearances for any conductor of a line operating at 300,000 or more volts 15 feet

Note: Added November 6, 1992 by Resolution SU-15 and revised September 20, 1996 by Decision No. 96-09-097.